

*Computer Science and Mathematics*  
Summer term 2017

**Exercises 6**

1. How much digital storage capacity would be necessary for the content of a library with 100,000 books, if we assume that each book has 200 pages, each page has 50 lines and each line has 80 characters, and if a 1-byte ASCII code is used for the characters?
  
2. Find the 8-bit two's complement representation of the negative integer  $-84$ .
  
3. For a binary representation of genetic information, the four bases from DNA, adenine (A), thymine (T), guanine (G) and cytosine (C), are simply encoded by the 8-bit ASCII codes of their first letters (A = 01000001, etc.).
  - (a) What is the redundancy of this code, if we assume that the four bases occur with equal frequencies? (In the calculation of  $H_0$ , consider all possible 8-bit blocks as symbols of the alphabet.)
  - (b) Give a non-redundant binary code for A, T, G, C.